

FULBOOST

Datasheet

FULBAT™

BATTERY CHARGERS



MULTI-FUNCTION LITHIUM BOOSTER

SPECIFICATIONS

Capacity	Current peak	Current start
15000 mAh	600 Ah	300A

FULBOOST is a multi-function lithium booster for vehicles equipped with WET, MF, SLA, GEL, Ca/Ca, AGM and EFB 12V lead acid battery. It can start engines up to 5.0L Gasoline and 3.0L Diesel.

Its power supply function allows to charge all types of electrical appliances with USB port.

Its torch function offers 3 lights mode : standard, SOS, flash

FEATURES

- Booster for 12V vehicles
- Charger for all types of electrical appliances
- 3 light modes
- Smart cables technology that protect the battery and onboard electronics
- Anti-spark technology, protection against short-circuit
- Protection against polarity reversal

BOX CONTENT

- Protective storage case
- Smart cable
- Multiconnectors USB cable
- Cigarette plug leadset
- 12V Home charger
- 8 PC supply connectors


BOOSTER

Booster for 12V vehicles*
(light gas & diesel engine vehicles)**



POWER SUPPLY

Charger for all types of electrical appliances



TORCH

3 light modes available: standard, SOS, flash



* For vehicle equipped with WET, MF, SLA, GEL, Ca/Ca, AGM or EFB 12V lead acid battery.

** Up to 5.0L gasoline engine and up to 3.0L diesel engine.