

SLA RANGE

Ready to use & non-spillable

SLA battery range is designed to offer maximum performance and safety! Ready to use, the Sealed Lead Acid (SLA) battery will not require any acid handling, initial preparation or maintenance. Its non-spillable design linked to its high performance make it the ideal battery for all ride-on mowers.

FEATURES


- AGM technology (factory activated)
- Ready to use
- 100% maintenance free
- Non-spillable: easy to ship
- Higher cycle life
- Ultra safe & highly vibration resistant
- Minimized plate sulfation
- Suitable for cold weather



COMPATIBLE CHARGERS

- Fulload 1000
- Fulbank 2000
- Fulload F4

NON-SPILLABLE



| Designation | P/N | Voltage (V) | Capacity Ah (10h) | Capacity Ah (20h) | CCA (A) | Dimensions (±2mm) | | | Polarity | Terminal 3D |
|-----------------------|--------|-------------|-------------------|-------------------|---------|-------------------|-----|-----|----------|-------------|
| | | | | | | L | W | H | | |
| U1-9 SLA (12N24-4A) | 550901 | 12 | - | 28 | 300 | 195 | 125 | 176 | + | |
| U1R-9 SLA (12N24-3A) | 550902 | 12 | - | 28 | 300 | 195 | 125 | 176 | - | |
| U1-12 SLA (12N24-4A) | 550903 | 12 | - | 32 | 400 | 195 | 125 | 176 | + | |
| U1R-12 SLA (12N24-3A) | 550904 | 12 | - | 32 | 400 | 195 | 125 | 176 | - | |
| SLA12-18 | 550633 | 12 | 18 | 18.9 | 150 | 182 | 77 | 168 | - | |
| SLA12-20 | 550879 | 12 | 20 | 21.1 | 180 | 182 | 77 | 168 | - | |
| SLA12-22 | 550907 | 12 | 22 | 23.1 | 210 | 182 | 77 | 168 | - | |
| FTX16 | 550763 | 12 | 14 | 14.7 | 230 | 150 | 87 | 161 | + | |
| FTZ7S | 550635 | 12 | 6 | 6.3 | 130 | 113 | 70 | 105 | - | |
| FB14L-A2 (12N14-3A) | 550927 | 12 | 14 | 14.7 | 175 | 135 | 90 | 167 | - | |
| FB14-A2 (12N14-4A) | 550946 | 12 | 14 | 14.7 | 175 | 135 | 90 | 167 | + | |
| F50-N18L-A (12N18-3A) | 550982 | 12 | 21 | 22.1 | 350 | 205 | 87 | 162 | - | |
| 53030 (F60-N30L-A) | 550945 | 12 | 30 | 31.6 | 300 | 178 | 123 | 166 | - | |
| 53034 (F60-N30-A) | 550843 | 12 | 30 | 31.6 | 300 | 178 | 123 | 166 | + | |